

STRADA-2X2-SCL

Type II/III (long) beam for very wide pole to pole distances. Ideal for pedestrian paths and residential roads. EN13201 P-classes.

TECHNICAL SPECIFICATIONS:

Dimensions 50.0 mm Height 7.8 mm

Fastening screw, pin

Colour clear

Box size 480 x 280 x 300 mm

Box weight 8.3 kg

Quantity in Box 800 pcs


ROHS compliant yes 1



MATERIAL SPECIFICATIONS:

ComponentTypeMaterialColourSTRADA-2X2-SCLLensPMMAclear






PHOTOMETRIC DATA (MEASURED):

bridgelux.

LED SMD 5050 FWHM Asymmetric

Efficiency 94 %
Peak intensity 0.630 cd/lm
Required components:






COMET

LED QUICK FLUX XTP 2x4 xxx LS G5

FWHM Asymmetric

Efficiency 94 %
Peak intensity 1.000 cd/lm


Required components:



CONST

LED QUICK FLUX XTP 2x6 xxx LS G5


FWHM Asymmetric
Efficiency 94 %
Peak intensity 1.000 cd/lm
Required components:



CONET

LED QUICK FLUX XTP 2x8 xxx LS G5

FWHM Asymmetric
Efficiency 94 %
Peak intensity 1.000 cd/lm
Required components:



PHOTOMETRIC DATA (MEASURED):

CREE 💠


LED XD16

FWHM Asymmetric

Efficiency 94 %

Peak intensity 1.100 cd/lm

Required components:



CREE \$

LED XD16 2x2 cluster


FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.750 cd/lm

Required components:





CREE \$


LED XP-G2

FWHM Asymmetric

Efficiency 94 %

Peak intensity 1.200 cd/lm

Required components:




CREE 💠

LED XP-G3

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.970 cd/lm



PHOTOMETRIC DATA (MEASURED):

CREE 💠


LED XP-L

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.900 cd/lm

Required components:



CREE \$

LED XP-L


FWHM Asymmetric

Efficiency 78 %

Peak intensity 0.550 cd/lm

Required components:

Undefined Manufacturer: Protective Plate, Glass



CREE 💠


LED XP-L2

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.750 cd/lm

Required components:




ULG Innotek

LED H35C1 (LEMWA33)


FWHM Asymmetric Efficiency 94 %

Peak intensity 1.100 cd/lm





PHOTOMETRIC DATA (MEASURED):



PHOTOMETRIC DATA (MEASURED):


WNICHIA

LED NVSxE21A **FWHM** Asymmetric

Efficiency 94 %

Peak intensity 0.380 cd/lm

Required components:




LED PrevaLED Brick DC 2x8

FWHM Asymmetric

94 % Efficiency

Peak intensity 1.100 cd/lm

Required components:



OSRAM Opto Semicond


LED Oslon Square Gen3

FWHM Asymmetric

94 % Efficiency

Peak intensity 1.100 cd/lm

Required components:



OSRAM Opto Semiconductors


LED

Oslon Square PC

FWHM Asymmetric

94 % Efficiency

Peak intensity 0.900 cd/lm



PHOTOMETRIC DATA (MEASURED):

PHILIPS

LED Fortimo FastFlex LED board 2x8 DA G4

FWHM Asymmetric Efficiency 94 %

Peak intensity 1.000 cd/lm Required components:

SAMSUNG


LED LH351B

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.860 cd/lm

Required components:



SAMSUNG


LED LH351C

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.900 cd/lm

Required components:




SAMSUNG

LED LH351D

FWHM Asymmetric

Efficiency 93 %

Peak intensity 0.740 cd/lm



PHOTOMETRIC DATA (MEASURED):

SAMSUNG


LED LH508A

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.700 cd/lm

Required components:






LED Z8Y22

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.870 cd/lm

Required components:






LED Z8Y22P

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.960 cd/lm

Required components:




TRIDONIC

LED RLE G1 49x121mm 2000lm xxx EXC OTD

FWHM Asymmetric

Efficiency 94 %

Peak intensity 0.900 cd/lm




PHOTOMETRIC DATA (MEASURED):

TRIDONIC

LED RLE G1 49x133mm 2000lm xxx EXC OTD


FWHM Asymmetric
Efficiency 94 %
Peak intensity 0.900 cd/lm
Required components:



TRIDONIC

LED RLE G1 49x223mm 4000lm xxx EXC OTD


FWHM Asymmetric
Efficiency 94 %
Peak intensity 0.900 cd/lm
Required components:



TRIDONIC

LED RLE G1 49x245mm 4000lm xxx EXC OTD


FWHM Asymmetric
Efficiency 94 %
Peak intensity 0.900 cd/lm
Required components:



TRIDONIC

LED RLE G2 HP 2x8 4000lm

FWHM Asymmetric Efficiency 94 % Peak intensity 1.000 cd/lm Required components:




PHOTOMETRIC DATA (SIMULATED):

CREE 💠

LED XB-H

FWHM Asymmetric


Efficiency %
Peak intensity cd/Im
Required components:



CREE 🕏

LED XHP35 HD FWHM Asymmetric

Efficiency %
Peak intensity cd/lm
Required components:




CREE 🕏

LED XM-L2

FWHM Asymmetric

Efficiency %
Peak intensity cd/Im
Required components:




CREE 💠

LED XP-E2

FWHM Asymmetric

Efficiency 91 %

Peak intensity 0.660 cd/lm




PHOTOMETRIC DATA (SIMULATED):

CREE 💠

LED XP-L HI FWHM Asymmetric

Efficiency %
Peak intensity cd/lm
Required components:




CREE 🚓

LED XT-E

FWHM Asymmetric

Efficiency %
Peak intensity cd/lm
Required components:




LG Innotek

LED H35C1 (LEMWA33)

FWHM Asymmetric
Efficiency 91 %
Peak intensity 0.740 cd/lm


Required components:



DESCRIPTION LUMILEDS

LED LUXEON 5258 FWHM Asymmetric

Efficiency %
Peak intensity cd/lm
Required components:




PHOTOMETRIC DATA (SIMULATED):

WNICHIA

LED NVSW219D FWHM Asymmetric

Efficiency 91 %
Peak intensity 0.660 cd/lm

Required components:




WNICHIA

LED NVSxx19B/NVSxx19C

FWHM Asymmetric Efficiency 87 %

Peak intensity 0.830 cd/lm

Required components:




WNICHIA

LED NVSxx19B/NVSxx19C

FWHM Asymmetric
Efficiency 69 %
Peak intensity 0.510 cd/lm

Required components:

Undefined Manufacturer: Protective Plate, Glass



OSRAM Opto Semiconductors


. __

LED Duris S8
FWHM Asymmetric
Efficiency 76 %

Peak intensity 0.440 cd/lm

Required components:

Undefined Manufacturer: Protective Plate, Glass



PHOTOMETRIC DATA (SIMULATED):


OSRAM Opto Semiconductors

LED Duris S8 FWHM Asymmetric

Efficiency 92 %

Peak intensity 0.620 cd/lm

Required components:




OSRAM Opto Semiconductors

LED OSCONIQ P 3737 (3W version)

FWHM Asymmetric Efficiency 91 %

Peak intensity 0.710 cd/lm

Required components:



PHILIPS


LED Fortimo FastFlex LED board 2x8 DAX G4

FWHM Asymmetric

Efficiency 90 %

Peak intensity 0.760 cd/lm

Required components:




SAMSUNG

LED LH181B

FWHM Asymmetric

Efficiency 92 %

Peak intensity 0.830 cd/lm






PHOTOMETRIC DATA (SIMULATED):

SEOUL SENICONDUCTO

LED Z5M1/Z5M2 FWHM Asymmetric

Efficiency %
Peak intensity cd/Im
Required components:




TOSHIBA
Leading Innovation >>>

LED TL1L4

FWHM Asymmetric

Efficiency %
Peak intensity cd/lm
Required components:





GENERAL INFORMATION:

NOTE: The typical beam angle will be changed by different color, chip size and chip position tolerance. The typical total beam angle is the full angle measured where the luminous intensity is half of the peak value.

MATERIALS:

As part of our continuous research and improvement processes, and to ensure the best possible quality and availability of our products, LEDiL reserves the right to change material grades without notice.

PRODUCT DATA USER AGREEMENT AND DISCLAIMER:

The measured data in the provided downloadable LEDiL Product Datasheets and Mechanical 2D-Drawings is rounded and provided as reference for planning. LEDiL Oy's optical specifications have been verified by conducting performance testing of the products in accordance with the company's quality system. The reported data are averaged results of multiple measurements with typical variation. LEDiL Oy reserves the right to without prior notification make changes and improvements to its products.

LEDiL Oy assumes neither warranty, nor guarantee nor any other liability of any kind for the contents and correctness of the provided data. The provided data has been generated with highest diligence but the provided data may in reality not represent the complete possible variation range of all intrinsic parameters. Therefore, in certain cases a deviation from the provided data could occur.

LEDiL Oy reserves the right to undertake technical changes of its products without further notification which could lead to changes in the provided data. LEDiL Oy assumes no liability of any kind for the possible deviation from any provided data or any other damage resulting from the usage of the provided data.

The user agrees to this disclaimer and user agreement with the download or usage of the provided files.

LEDIL Oy

Joensuunkatu 13 FI-24240 SALO Finland

LEDiL Inc.

228 West Page Street Suite D Sycamore IL 60178 USA

Local sales and technical support

www.ledil.com/ where_to_buy

Shipping locations

Salo, Finland Hong Kong, China

Distribution Partners

www.ledil.com/ where_to_buy